


Grounding Lug with U-Shape Copper Channel

- Assembly -



Fix Grounding Lug into either top or side rail channel.



Insert U-Shape Copper Channel into Grounding Lug.



Strip earthing cable and insert the conductor into copper channel. Tighten the bolt of M6*14 to ensure the earthing cable is tight.

- Component -



Grounding Lug, with Clenergy Logo, with U-Shape Copper Channel

Part No.: EZ-GL-ST/UC (bar code:13-14030-037)

- Technical Specification -

Application	For Clenergy' s PV Mounting System
Fixing method	Fixing into ECO/T50/T110 Rail with Z module
Cable Size	4, 6 and 10 mm ²
Dimensions	W23mm*L45mm
Weight	0.095 kg
Packaging	80 units per pack, 4 packs (320 units) per carton
Material	Lug: Hpb59-1 U-Shape Copper Channel: T2 Copper Bolt/Washer: SUS304 Z module: AL6005-T5
Standard	AS NZS1170.2-2011

